

## Release Note

This document describes upgrades and known issues related to a new release of Radiocrafts Industrial IP Mesh (RIIM™) SDK, and the included platform images and examples

## Known Issues

Revision	Issue	Workaround
1.0.0 and prior	The Boarder Router platform has a built-in driver for Ethernet connection, and therefore needs to be connected to a working Ethernet Controller.  It is not necessary to connect an Ethernet cable	Connect a Microchip ENC28J60-I/ML (and associated hardware) to the module via SPI. <b>or</b> Use Radiocrafts RC1882-BRB.
1.2.0 and prior	Setting PAN ID in TSCH platforms does not work	Use default PAN ID (0x9812)
2.0.0	TSCH Mesh routers occasionally reset during joining phase	None. Nodes are stable when part of a network
3.0.0	Using I2C and UART together introduces extra byte in UART buffer	Disable UART when using I2C and vice versa
	Sending UDP packets using IPv4 addressing does not work	Use IPv6 addressing instead. To use IPv4 addressing, the prefix should be 64:FF9B . The last 4 bytes in the IPv6 address must be the actual IPv4 address
	Lost packet retransmission too slow in TSCH. This can lead to congestion if packets are sent too frequently	Do not send packets more often than every 10 seconds
3.1.0	Using multicast sometimes crashes the module	None. Do not use multicast.
3.1.0 and prior	TSCH timing between nodes may drift too much resulting in nodes disjoining network	Set Network.setTschMaxBroadcastRate to 16 or lower
3.2.0	For the border router, call to the Clock API can only be made > 100ms after StartBorderRouter command	Ensure access of the Clock API after 100ms using for instance Timer callbacks ( Timer.create(...) )

## Product Change Notification

Radiocrafts defines product changes by:

- C:** Correction of an existing feature
- N:** Introduction of new features
- P:** Performance improvement

Revision	Changes	Date
0.9.1	<b>N</b> New product pre-release	2019-07-05
1.0.0	<b>N</b> New product release <b>N</b> Sleepy leaf nodes supported <b>N</b> Added new examples ICI applications <b>P</b> Improved building system for ICI application by introducing easy to use click-> compile_and_upload functions <b>P</b> Updated most of the documentation for better readability and more detailed description	2019-09-24
1.1.0	<b>C</b> Product update, new features and enhancements <b>N</b> New platform for Border Routers without Microchip ENC28J60 <b>N</b> UDP API added <b>N</b> CoAP packet without response added ("Fire and forget") <b>N</b> Multicast support added <b>N</b> Link layer security (LLSEC) added <b>N</b> Added static port maps in Border Router for easy direct access to all nodes from the outside (Ethernet) network <b>N</b> Added Robustness Factor for network stability <b>P</b> Stability fixes	2020-02-28
1.2.0	<b>C</b> Product update, new features and enhancements <b>N</b> Default startup output power set to 0 dBm <b>N</b> Channel hopping (TSCH) for 868 and 915 MHz <b>N</b> Single Channel (CSMA) supports both 868 and 915 MHz <b>N</b> Support for RC1882, RC1882HP and RC1892HP <b>N</b> Added UDP example <b>P</b> Stability fixes	2020-04-30
2.0.0	<b>N</b> Product update, new features and enhancements <b>N</b> Added redundant border router example <b>N</b> Added transparent UART example <b>N</b> Added EEPROM example <b>N</b> Added Clock example <b>P</b> Split upload platform scripts into TSCH and Single Channel  <b>N</b> Added Clock API and Clock CoAP resource <b>P</b> User defined CoAP resources increased from 1 to 5 <b>N</b> Added SLIP connection <b>N</b> Added possibility to read voltage input (Battery) <b>P</b> Increased number of GPIO handlers to 9 (all GPIOs) <b>N</b> Added support for 1-hop multicast <b>P</b> Stability fixes <b>N</b> Added Adaptive Frequency Agility <b>N</b> Added Listen Before Talk	2021-02-01

3.0.0	<p><b>N</b></p> <p><b>N</b></p> <p><b>N</b></p> <p><b>C</b></p> <p><b>N</b></p> <p><b>C</b></p> <p><b>P</b></p> <p><b>P</b></p> <p><b>N</b></p> <p><b>N</b></p> <p><b>N</b></p> <p><b>N</b></p> <p><b>P</b></p>	<p>Product update, new features and enhancements</p> <p>Added TX/RX pin control on UART for RS485</p> <p>Added new UART termination criteria/parameters for reception (RX):</p> <ul style="list-style-type: none"> <li>• Intra byte timeout</li> <li>• Total transmission timeout</li> <li>• Termination byte</li> <li>• Use of length byte</li> </ul> <p>Wake on UART</p> <p>GPIO responds(wakes up) faster in sleeping nodes</p> <p>User can get node reset reason</p> <p>Removed RSSI measurement in network links</p> <p>Reduced power consumption in TSCH sleeping mesh routers from minimum 180 uA to minimum 118 uA</p> <p>Improved throughput in TSCH mode for data to border router.</p> <p>Examples updated</p> <p>Added possibility to get and set Ethernet MAC address</p> <p>New frequency bands for Vietnam and India</p> <p>New selectable predefined TSCH settings:</p> <ul style="list-style-type: none"> <li>• Low power</li> <li>• Balanced</li> <li>• Low Latency</li> <li>• High throughput</li> </ul> <p>Stability and bug fixes</p>	2021-09-17
3.1.0	<p><b>N</b></p> <p><b>C</b></p> <p><b>C</b></p> <p><b>C</b></p>	<p>Product update, new features and enhancements</p> <p>Microsoft Visual Code integration</p> <p>Faster retransmission of lost packets in TSCH</p> <p>Fixed issue with corrupt UART buffers when used together with I2C</p> <p>UDP with IPv4 is fixed</p>	2021-11-12
3.2.0	<p><b>C</b></p> <p><b>P</b></p> <p><b>P</b></p> <p><b>C</b></p> <p><b>N</b></p> <p><b>N</b></p> <p><b>N</b></p> <p><b>C</b></p> <p><b>N</b></p> <p><b>P/C</b></p>	<p>Product update, new features and enhancements</p> <p>getNetworkState always returns ONLINE for BR</p> <p>Multicasts can now be sent continuously without the need for occasional longer pauses</p> <p>Network.setMaxBroadcastRate changes EB interval quicker</p> <p>Crash when using multicast fixed</p> <p>Setting PANID to 0xFFFF makes the node attempt to join networks with any other PANID</p> <p>TSCH parameters can be set/changed in an active network</p> <p>GPIO now has PWM control</p> <p>UDP port number improvement when using Ethernet and IPv4</p> <p>Added 2 new examples in SDK:</p> <ul style="list-style-type: none"> <li>• Auto joining using PANID 0xFFFF</li> <li>• CoAP sprinkler example</li> </ul> <p>Better TSCH timing synchronization between nodes</p>	2022-02-11

## Disclaimer

Radiocrafts AS believes the information contained herein is correct and accurate at the time of this printing. However, Radiocrafts AS reserves the right to make changes to this product without notice. Radiocrafts AS does not assume any responsibility for the use of the described product; neither does it convey any license under its patent rights, or the rights of others. The latest updates are available at the Radiocrafts website or by contacting Radiocrafts directly.

As far as possible, major changes of product specifications and functionality, will be stated in product specific Errata Notes published at the Radiocrafts website. Customers are encouraged to check regularly for the most recent updates on products and support tools.

## Trademarks

RIIM is a trademark of Radiocrafts AS.

All other trademarks, registered trademarks and product names are the sole property of their respective owners.

## Life Support Policy

This Radiocrafts product is not designed for use in life support appliances, devices, or other systems where malfunction can reasonably be expected to result in significant personal injury to the user, or as a critical component in any life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness. Radiocrafts AS customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Radiocrafts AS for any damages resulting from any improper use or sale.

## Radiocrafts Support:

Knowledge base: <https://radiocrafts.com/knowledge-base/>

Application notes library: <https://radiocrafts.com/resources/application-notes/>

Whitepapers: <https://radiocrafts.com/resources/articles-white-papers/>

Technology overview: <https://radiocrafts.com/technologies/>

RF Wireless Expert Training: <https://radiocrafts.com/resources/rf-wireless-expert-training/>

## Contact Radiocrafts

Sales requests: <https://radiocrafts.com/contact/>

© 2022, Radiocrafts AS. All rights reserved.